

**Use Small female
 Sockets [EL-MS0124] / A31995-ND.
 And install from this end
 (the threaded side)**


Note: Unless otherwise specified
 cut length +/- 3mm
 Molex strip length +/-0.5mm
 Ferrule strip length +/-0.5mm
 Ring terminal strip length +/-0.5mm



1x [EL-MS0133]
 CONN, RCPT, 14 POS w/Brass Inserts



9x [EL-MS0124]
 20-24 AWG Tin Sockets for Receptacle

All wires this side
 Strip 4mm



- 4x [EL-MS0059] Female Molex Pin
- 1x [EL-MS0062] Female 4pin Housing
- Strip 4mm
- Pin 1
- Pin 2
- Pin 3
- Pin 4
- 1x [PC-CN0032] Term Block Plug 2POS
- 2x [EL-MS0362] 24 AWG 6.0mm Pin Length Single Wire Insulated Ferrule
- Pin 1
- Pin 2
- 2x [EL-MS0059] Female Molex Pin
- 2x [PC-CN0001] Female 2pin Housing
- Pin 1
- Pin 2
- 1x [EL-MS0141] Term Ring Non Ins 26-22AWG

Initial	comments	date	Rev
JW	update bom to have correct lengths of gray wire and black wire	03/25/19	A

DRAWN BY: West		DATE	 	
CHECKED BY		DATE		
EL-HR0176			TITLE CB Dual Extruder Harness	
FILE NAME EL-HR0176_CB_Dual_Extruder_Harness_revA.odg		SHEET 1	REV. A	

AO part number	qty	UoM	Supplier	supplier pn
EL-WR0099	130	mm	Allcable	C0762A.41.10
EL-MS0133	1	pce	TTI global	211103-1
EL-MS0124	9	pce	TTI global	1-66331-4
EL-MS0059	6	pce	TTI global	16-02-0086
EL-MS0062	1	pce	Sager	50579404
PC-CN0032	1	pce	TTI global	395300002
EL-MS0362	2	pce	Digikey	FSD74-8-D
PC-CN0001	1	pce	Sager	50579402
EL-MS0141	1	pce	TTI global	P22-4R-M
EL-WR0103	200	mm	Allcable	HU1569247RD
EL-WR0104	260	mm	Allcable	HU1569247OE
EL-WR0105	100	mm	Allcable	HU1569247BK